

AMENDMENTS TO THE CLAIMS:

This listing of claims will replace all prior versions, and listings, of claims in the application.

LISTING OF CLAIMS:

1. (Currently Amended) A signal receiver having calibration for a frequency dependent I/Q phase error, comprising:

a calibration tone generator for generating a calibration tone for providing in-phase (I) and quadrature phase (Q) tone components;

I and Q filters for filtering said I and Q calibration tones for issuing filtered I and Q output tones having an undesired frequency dependent I/Q phase error, at least one of the I and Q filters having an adjustable characteristic; and

a correlator for cross correlating said I and Q output tones for providing a cross correlation feedback signal, said correlation feedback signal used for adjusting said adjustable characteristic for reducing said frequency dependent I/Q phase error; wherein

said I and Q filters include an I analog filter for providing said I output tone and a Q analog filter for providing said Q output tone and said adjustable characteristic is a cutoff frequency of at least one of said I and Q analog filters.

2. (Original) The receiver of claim 1, wherein:

said correlation feedback signal adjusts said adjustable characteristic for minimizing a phase difference between said I output tone and said Q output tone.

3. (Original) The receiver of claim 1, wherein:

said calibration tone has a frequency near to a cutoff frequency for said I and Q filters.

4. (Cancelled).

5. (Currently Amended) The receiver of claim 41, wherein:

said cutoff frequency is adjusted by frequency scaling at least one pole and at least one zero of said at least one of said I and Q analog filters by a certain common factor.

6. (Currently Amended) The receiver of claim 41, wherein:

said certain common scale factor is adjusted by adjusting channel resistance of at least one transistor.

7. (Original) The receiver of claim 1, wherein:

the I and Q filters include I and Q allpass filters for providing said I and Q output tones; and

said adjustable characteristic is a phase delay of at least one of said I and Q allpass filters.

8. (Original) The receiver of claim 7, wherein:

said phase delay is adjusted by frequency scaling at least one pole by a certain factor and frequency scaling at least one zero by an inverse of said certain factor in said at least one of said I and Q allpass filters.

9. (Original) The receiver of claim 1, further comprising:

a frequency downconverter including a local oscillator for providing a complex LO signal and I and Q frequency downconverters using said LO signal for downconverting an input signal having a carrier frequency to I and Q signal components; and wherein:

the calibration tone generator issues a calibration signal as said input signal having a certain frequency offset from said carrier frequency for providing said I and Q calibration tone components in place of said I and Q signal components.

10. (Currently Amended) A method for correcting frequency dependent I/Q phase error, comprising:

- generating a calibration tone for providing in-phase (I) and quadrature phase (Q) tone components;
- filtering said I and Q calibration tones for providing filtered I and Q output tones having undesired frequency dependent I/Q phase error, comprising:
 - filtering said I calibration tone component with an I analog filter for providing said I output tone; and
 - filtering said Q calibration tone component with a Q analog filter for providing said Q output tone;
- cross correlating said I and Q output tones for providing a cross correlation feedback signal; and
- adjusting an adjustable characteristic of at least one of the I and Q filters with said correlation feedback signal for reducing said frequency dependent I/Q phase error comprising adjusting a cutoff frequency of at least one of said I and Q analog filters.

11. (Original) The method of claim 10, wherein:

- the step of adjusting said adjustable characteristic includes minimizing a phase difference between said I output tone and said Q output tone.

12. (Original) The method of claim 10, wherein:

- said calibration tone has a frequency near to a cutoff frequency for said I and Q filters.

13. (Cancelled)

14. (Currently Amended) The method of claim ~~13~~10, wherein:

the step of adjusting said cutoff frequency includes frequency scaling at least one pole and at least one zero of said at least one of said I and Q analog filters by a certain common factor.

15. (Currently Amended) The method of claim ~~43~~10, wherein:

said step of frequency scaling includes adjusting channel resistance of at least one transistor.

16. (Original) The method of claim 10, wherein:

the step of filtering said I and Q calibration tone components includes passing the I and Q calibration tones through I and Q allpass filters for providing said I and Q output tones; and the step of adjusting said adjustable characteristic includes adjusting a phase delay of at least one of said I and Q allpass filters.

17. (Original) The method of claim 16, wherein:

the step of adjusting said phase response includes frequency scaling at least one pole by a certain factor and frequency scaling at least one zero by an inverse of said certain factor in said at least one of said I and Q allpass filters.

18. (Original) The method of claim 10, further comprising:

frequency downconverting an input signal having a carrier frequency with a complex LO signal to I and Q signal components; and wherein:

the step of generating said calibration tone includes issuing a calibration signal as said input signal having a certain frequency offset from said carrier frequency for providing said I and Q calibration tone components in place of said I and Q signal components.